CROUZET

3 PHASE, PHASE CONTROL MWA

84873024
MWA PHASE CONTROL RELAY



- Triggers alarm upon incorrect phase sequence, phase interruption and asymmetry
- Adjustable line voltage
- Measures returned voltage to 70%
- 17.5 mm cabinet with DIN rail

PRODUCT DESCRIPTION

Control relay for phase monitoring with regeneration of voltage and asymmetry. Adjustable switch at the front for adjustment of correct voltage in 3-phase networks. Voltage switch's position is not registered until the operating voltage is switched on. If the switch position is changed during operation, all LEDs (LED indication) begin to flash but the unit will continue to function normally with the voltage that was set at the most recent power connection. The LEDs return to normal function when the correct voltage is restored. The relay monitors the correct phase sequence between the three phases or if any phase is lacking (measured U<0.7xUn), 70 % of the returned voltage. The asymmetry setting is made at the front between 5 and 15 % (the rated voltage between the phases Un x degree of asymmetry, %). In the event of an asymmetry fault, the relay triggers an alarm (drops out) after the time delay Tt that is set at the front by the user. Green LED (Un) indicates supply voltage OK. Yellow LED (R) indicates active relay output.

SPECIFICATIONS

Selection of rated voltage	208, 220, 380, 400, 415, 440, 480 V
Time Delay Alarm	0.2 s
Time Delay Start	0.5 s
Time Delay On Crossing The Threshold	0,1-10s

Output	Relay
Breaking capacity	5A, 250V AC/DC
Supply voltage	3 x 208-480V AC

IP Class Connection	IP20
IP Class Housing	IP30
Temperature range from	-20 °C
Temperature range to	50 °C

Temperature range bearing, from	-40 °C
Temperature range bearing, to	70 °C
Weight	80 g
Approvals	CSA, GL, RoHS, UL







